BT Versatility

Communication without complication

Click-to-Dial Installation & Configuration Guide



Programming the BT Versatility System

Start the Wizard and connect to the BT Versatility system From the main menu select System, Systemwide Settings

Save Close Current Pane Get all	and save! Load and send all! Reset Current Pane to Default	Disconnec
Set Range On Set Range Off Rece	ive Selected Receive on screen data Send Selected Send Changes	
Systemwide Settings		
	Setting	
System Programming Password	1111	
PABX Mode	Key System	
System Voice Box On		
Voice Box Password	1111	
UM Enabled		
UM Deletion Type	MS Outlook	
UM Email		
UM Email Password		
Click to Dial Key	10623D3E54214251443E1051	
Music On Hold	Internal Source	
Programming Position	Ext 20	
P.A Position		
Music on Hold Extension		
Central Bell 25Hz		
Activate Night Service		
Weekend Service		
Night Service 1 Start		
Night Service 1 End		
Night Service 2 Start		
Night Service 2 End		
Line key/Flashing on Hold	V	
Call Logging	off	
Call Logging XON/XOFF		
CLI Store (All Calls)		
V.24 Baud Rate	115200	
Valas Dav Canaska (40.00)	20	

Enter the Click to Dial Key. Select Extension Settings, Non-ISDN Features

Satt Range Oni Satt Range Oni Receive on screen data Sand Satected Send Changes Jon ISDN Features	Save Close Current Pane Get	all and save!	Load and send	all! Reset Curr	ent Pane to Def	ault		Disconnect
In ISDN Features Protect From Paging Protect From Paging Protect System Protect Protect Protec	Set Range On Set Range Off F	teceive Selecter	Receive on	screen data	Send Selected	Send Change	es	
Ext 20 Ext 21 Ext 22 Ext 23 Ext 24 Ext 25 Ext 35 Ring Frequency Setting 254z 2	Non-ISDN Features							
Protect From Paging Default 25Hz 25Hz 25Hz 25Hz 25Hz 25Hz 25Hz 25Hz		Ext 20	Ext 21	Ext 22	Ext 23	Ext 24	Ext 25	Ext 2
Ring Frequency Setting 25Hz	Protect From Paging							
Auto Detect Systemphones V V V V V V V V V V V V V V V V V V V	Ring Frequency Setting	25Hz	25Hz	25Hz	25Hz	25Hz	25Hz	25Hz
Personal Caller ID List	Auto Detect Systemphones	r		V				1
Voice Boxes V V V V V V V V V V V V V V V V V V V	Personal Caller ID List							
Kognat Feetback V V V V V V V Background Music Image: Constraint of Music Notifine Image: Constraint of Music Information Only Voice Box Image: Constraint of Music Image: Constraint of Music Image: Constraint of Music Image: Constraint of Music UM Enabled Image: Constraint of Music MS Outlook	Voice Boxes							
Default to Mid Volume Hotine Hot	Keypad Feedback	2		~		2		r
Background Music Backgr	Default to Mid Volume							
Hotline Motion Service Standard Standard Disabled Disabled Disabled Disabled Standard Standar	Background Music							
Voicemail Password 1111 1111 1111 1111 1111 1111 1111 1	Hotline							
Information Only Voice Box I I I I I I I I I I I I I I I I I I I	Voicemail Password	1111	1111	1111	1111	1111	1111	1111
UM Enabled Standard Standard Disabled D	Information Only Voice Box							
UM Deletion Type MS Outlook MS Ou	UM Enabled							
UME Email Pastword Click to Dial Service Standard Standard Disabled Disabled Disabled Disabled Disabled Standard	UM Deletion Type	MS Outlook	MS Outlook	MS Outlook	MS Outlook	MS Outlook	MS Outlook	MS Out
UM Email Password Click to Dial Service Standard Standard Disabled Disabled Disabled Disabled Disabled Disabled Disabled Disabled Standard	UM Email Address							
Click to Dial Service Standard Standard Disabled Disabled Disabled Disabled Disabled Disabled Disabled Disabled Standard	UM Email Password							
Disabled Standard	Click to Dial Service	Standard	Standard	Disabled 🔻	Disabled	Disabled	Disabled	Disable
Standard				Disabled				
arona a				Standard				
				Standard				

In Click to Dial Service, select Standard from the drop-down menu for each extension that you wish to enable for Click to Dial

Send Changes

Click-to-Dial setup is now complete on your BT Versatility phone system, however you must also allocate one VoIP endpoint on your Broadband Module to UM Service before the Click to Dial application will run on any of your PCs. (please refer to the Unified Communications Settings in the BT Versatility Broadband Module Manual)

PC Requirements

Windows ® Vista Operating System, Windows ® 2000 professional, Windows ® XP professional, or Windows ® 2003 server, Intel Pentium 4 or equivalent processor, 256 MB RAM, network interface card and a spare USB port (TypeA)

Installing and Configuring the Click-to-Dial Application

Insert the Click-to-Dial Installer disk into your PC CD drive.

Run		? 🛛
	Type the name of a program, folder Internet resource, and Windows wi	, document, or I open it for you.
Qpen:	200	~
	OK Cance	Browse

Select Start, Run, and browse to your CD drive



Select setup and Open



Select OK

Select Next >





Select "I accept the terms in the licence agreement"

Select Next>

🛃 BTV Cli	ck-to-Dial 1.0.01 - li	nstallShield Wiza	d	×
Connectio Network	on Details Connection Configuration	For PBX		Click-to-Dial
	Enter the network conne	ction information for t	ne telephone s	ystem
	Hostname / IP Address	192.168.1.1		
	Port	4000		
	Extension Number	21		
	Password	***		
InstallShield -		< <u>B</u> ack	<u>N</u> ext >	Cancel

Enter the following information:

Hostname/IP Address:	This IP address will be provided by the system administrator
Port:	Leave this at the default setting of 4000
Extension Number:	Enter your BT Versatility extension number
Password:	Enter the password (this is the same as the extension lock password which is 123 in default)

Click-to-Dial Installation & Configuration

Customer Information	Click-to-Di
Please enter your information.	
User Name:	
Terry Williams	
Organization:	
Lake Communications	

Enter your Name and Organization

Click Next >



Click Next >

🛱 BTV Click-to-Dial 1.0.01 - InstallShield Wizard	×
Ready to Install the Program The wizard is ready to begin installation.	Click-to-Dial
Click Install to begin the installation.	
If you want to review or change any of your installation settings exit the wizard.	, click Back. Click Cancel to
InstallShield	[nstall] Cancel

Click Install >



BTV Click-to-Dial has now been installed on your PC.

This icon will now appear in the bottom right lower toolbar

? _ 🗆 X 6 Click-to-Dial - 🗠 🛸 🗔 - 🗔 🖉 🗞 🛵 DSS All Calls Missed Calls Directory Туре Name Dial Description Number 📥 Search for specific entries in the directory 4031000 æ 2 2 0 Acapulco B 6771085 Acapulco R 2 0 Name Alan Beckw Alan Beckw 004478 2 Andrew C 0 Andrew C 006140 Number 4 Anna OR FR 0 Anna OR FR 1298 2 ANTHONY 0 ANTHONY 4031010 Reset Search 4 Anthony Be 9 Anthony Be 1010 Search in. 2 0 0872415 Anthony Mb Anthony Mb Anthony PC Anthony PC 4 0 1210 System Speed Dial 🔽 Extensions 0 42 Ballach Da Ballach Da 403114; Personal Directory Outlook 2 Benardo Mb 0 Benardo Mb 0874190 4 Bernardo 0 Bernardo 1116 -> -

Right click on the icon and select Phone Manager to display the application



Offices Wordwide

The telecommunications services described in this publication are subject to availability and may be modified from time to time. Services and equipment are provided subject to British Telecommunications pIc's respective standard conditions of contract.

Nothing in this publication forms any part of any contract.

©British Telecommunications plc 2008 Registerd office: 81Newgate Street, London EC1A 7AJ Registered in England No. 1800000

Part No. LR2726.31000-2

Printed in paper which meets international environmental standards.